



# PS210

- BUILT TO RUN UP TO 2 LOCKS, EXIT TRIM & LP MOTOR/SOLENOID DEVICES
- ROBUST SOLID-STATE OUTPUTS - PROTECTS SYSTEM RELAYS
- ROCK SOLID BOARD DESIGN IMPROVES RELIABILITY
- BUILT TO LAST IN THE USA

**PS210** - 110-120VAC input power supplies that deliver (1.5) amps @ 24VDC to (1) PTC fused outputs. (1) solid-state input triggers, protects system relays from shorts, grounds and surges. It's regulated linear design makes it a perfect match for electric locks, motor or solenoid driven exit devices, electric strikes, and mag locks.

## SPECIFICATIONS

### INPUT VOLTAGE:

- 120 VAC, 60 Hz,
- Input Fuse: 2 Amp Fuse @ 250VAC

### OUTPUT VOLTAGE:

- 2A @ 24VDC
- 1 Solid State I/O's - 2A auto resetting fused outputs
- Over-voltage protection
- Output Voltage trim pot

### FIRE ALARM:

- Fire alarm tie-in

### ELECTRICAL:

- Temperature range: 0 to 49° C; 32 to 120° F
- Maximum humidity: 85%

### LED's:

- Red = A/C Power indicator
- Green = D/C Output indicator

### FEATURES & BENEFITS:

- Linear design insures ample inrush/hold current for latch retraction
- Door mounted LED Power Indicator
- Easy to remove euro connectors

### LISTINGS:

- UL294 6<sup>th</sup> Edition

### MECHANICAL DETAILS:

- Enclosure dimensions: PS210 (11" W x 11" H x 4" D).
- 1/2" & 3/4" knockouts on all sides
- Hinge-less removable cover; Cam lock not provided
- Product Weight: PS210 - 10lbs
- Shipment Weight: PS210 - 11lbs

Part #	Easy Order #	Description
PS210	78850	w/o battery back up.

**U.S. Customer Support**  
 1-888-622-2377

**Visit our website for more details**  
[www.CommandAccess.com](http://www.CommandAccess.com)

**Canada Customer Support**  
 1-855-823-3002

## POWER SUPPLY MATRIX

	24VDC PS Line	Amperage(Continuous)	Boost Current <sup>5</sup>	Inputs	Outputs (fused)	Battery Back-up (Batteries Not Included)	Fire Alarm Link	24V Power Tap (Constant power)	Locking Hardware (Mortise/Cylindrical/Exit Trim)	Latch Retraction (with LPM, PM300HO)	Latch Retraction (with PM300/Solenoid)	Latch Retraction (with MM Module/Motor)	Metal Enclosure
UL294 6E	PS204	2	3	4	4	-	✓	-	4	-	-	4	S
	PS204B	2	3	4	4	✓	✓	-	4	-	-	4	L
	PS210	1.5	2.5	1	1	-	- <sup>1</sup>	-	2 <sup>2</sup>	2 <sup>2</sup>	2 <sup>2</sup>	2 <sup>2</sup>	S
	PS220	2	3	2	2	-	✓	✓	2	2	2	4	S
	PS220B	2	3	2	2	✓	✓	✓	2	2	2	4	L
	PS440B	4	6	4	4	✓	✓	-	4	3	4	4	L
	PS480B	4	6	8	8	✓	✓	-	8	0	8	8	L
UL294	PS1	1	-	1	1	-	- <sup>1</sup>	-	2 <sup>2</sup>	2 <sup>2</sup>	2 <sup>2</sup>	2 <sup>2</sup>	S
	PS2 <sup>4</sup>	2	-	2	2	-	✓	-	2	0	2	2	L
	PS2BB <sup>4</sup>	2	-	2	2	✓	✓	-	2	0	2	2	L
	PS5	5	-	0	1	✓	✓	-	8 <sup>3</sup>	6 <sup>3</sup>	8 <sup>3</sup>	8 <sup>3</sup>	L
	PS5-4	5	-	4	4	✓	✓	-	4	4	4	4	L
	PS5-8	5	-	8	8	✓	✓	-	8	0	8	8	L

**Small Enclosure: 11" x 11" x 4"**

**Large Enclosure: 13" x 15.5" x 5"**

1. Uses Fire Alarm tie-in through trigger.
2. 1 output powers 2 devices/locks simultaneously
3. Up to stated devices/locks depending on distribution board or relays (by others).

4. Add Suffix (BO) for board only. Will not include metal enclosure.
5. Boost Current: Max current allowed by UL at 20% duty cycle.